
# AQUA MATIC Dual Pass



Introducing our new and most revolutionary member of the Sea Recovery Family. Specialized for those demanding ultra-pure and clean potable water.



Use Ultra-Pure Water to Leave Your Boat Spotless and Clean

# **FEATURING:**

- Highest Capacity to Footprint/Weight Ratio.
- Up to 3400 GPD from Sea Water
- Self-Contained, Plug and Play System
- Titanium High Pressure Pump Provides an Extended Life Cycle with Salt Water Compatibility and Quiet Operations
- Flexible Installation and Easy to Operate
- Globally Supported by a Network of More than 300 Dealers and Distributors







- 8-Inch Colored Touch Screen Remote Mounted
- Real Time Water Quality Monitor
- Screens are Available in Multiple Languages

# Dimensions - Aqua Matic Dual Pass


# Front




#### Touch Screen Controller




## Top view




## Membrane Assembly - Sea Water




#### Pre-Filter Assembly




## Booster Pump




#### Doc Water Feed



#### SW / FWF Feed



#### Membrane Assembly - Tap Water



# Specifications - Aqua Matic DP

Model #	Fresh Water Production from sea water	Ultra Pure Water Production from sea water	Ultra Pure Water Production from dock water	Weight
A400C-1800GPD-1400GPD	1800 GPD   6814 LPD	1400 GPD   5300 LPD	900 GPD   3407 LPD	413 lbs / 187 kg
A400C-2600GPD-2200GPD	2600 GPD   9842 LPD	2200 GPD   8328 LPD	1700 GPD   6435 LPD	413 lbs / 187 kg
A400C-3400GPD-2900GPD	3400 GPD   12870 LPD	2900 GPD   10978 LPD	2400 GPD   9080 LPD	428 lbs / 194 kg

<sup>\*</sup> Production may vary +/-20% | GPD: Gallons per day • LPD: Liters per day | \* Based on 60 psi (4Bar) Dock Water Pressure.

## **ELECTRICAL**

Pump Motor /HP	Voltage VAC	Hz	Phase*	Normal Operating Amps	Start Up Current
Booster 1.5/2	220/380//230/460	50//60	3	4.8/2.4//5/2.5	14/7.2//15/7.5
Booster 1.5/1	115/230	50//60	1	14.2/7.1//18.2/9.1	54

Model #	Pump Motor / HP	Voltage VAC	Hz	Phase*	Normal Operating Amps	Start Up Current	Circuit Breaker Amp
1800/1400	5	190/380//230/460	50/60	3	15.6/7.8//13.4/6.7	47/24//40/20	51/26/46/23
2600/2200-3400/2900	5//7.5	190/380//230/460	50/60	3	16.2/8.1/19/9.5	49/25//57/29	53/27//60/30
1800/1400	5	220/230	50/60	1	24/21.8	72/66	83/73



2630 E. El Presidio St., Carson, CA 90810
Toll Free: (855) 339-6899 • Tel: (310) 608-5600
Fax: (310) 608-5692 • Email: waterpurification@parker.com
Web: www.searecovery.com | www.parker.com/watermakers