

**Motor housings are over-molded in plastic to provide maximum protection from corrosion. 5 Year Warranty. 123 dB(A) rating. 12 volt, pre-wired, dual trumpet horns with sealed sound units. 100% stainless steel exteriors with 304 stainless steel diaphragms.**

For a **FREE** catalog of Marinco Recreational Group products, contact your local dealer or Marinco.

**Marinco**

2655 Napa Valley  
Corporate Drive  
Napa, California 94558

Phone: 707-226-9600  
Fax: 707-226-9670  
Website: www.marinco.com

For more information and installation guides  
visit our website: [www.marinco.com](http://www.marinco.com)

Product No. 10029XLP

Made in Thailand  
20381 (9/03)



## INSTALLATION AND WIRING INSTRUCTIONS

### INSTALLATION:

1. Select an installation position on the boat where a minimum of spray will hit the horns when the boat is underway.
2. At the same time, select an installation position which will assure the shortest possible length of wire from the horns to the power source.
3. Use the holes in the bracket as a template for the location of the mounting points and drill holes for the bracket and wiring.
4. Insert wiring through the deck, then install the bracket to the deck surface. Caulk all installation holes with silicone sealer. **Be sure the trumpets point slightly downward to permit water drainage.**

### WIRING:

1. Connect wiring as illustrated in the diagram.
2. Cut wires of sufficient length to avoid any tension at the connecting points.
3. Use flexible stranded wire of sufficient size as per wiring chart.
4. If horn volume is weak, recheck wiring connections and ground wire. If horn does not work at all, check the fuse.

### RECOMMENDED WIRE SIZES FOR 12 VOLT OPERATION

Wire Length**	Wire Size	Wire Length**	Wire Size
0-25 feet	14 AWG*	0-8 meters	1.9 mm
26-40 feet	12 AWG	9-12 meters	2.3 mm
41-60 feet	10 AWG	13-18 meters	3.0 mm
over 60 feet	8 AWG	over 18 meters	4.0 mm

\* AWG: American Wire Gauge

\*\* As measured from the battery to the horn and back to the battery (round trip).

Horn wiring has no polarity, negative or positive can be attached to either wire.

