# Sea Recovery Aqua Matic Dual Pass


Mid to Mega Yachts (40 - over 80 ft / 12 - over 24 m)



## Tomorrow's Technology, Here Today

Introducing our new and most revolutionary member of the Sea Recovery Family. Specialized for those demanding ultra-pure and clean potable water.

Use Ultra-Pure Water to Leave Your Boat Spotless and Clean







## **Contact Information:**

Parker Hannifin Corporation **Water Purification** 2630 E. El Presidio Street Carson, CA 90810

phone 310 608 5600 fax 310 608 5692 waterpurification@parker.com

#### Website:

www.parker.com/waterpurification

#### Sales:

waterpurification@parker.com

#### **Tech Support:**

watertech@parker.com

## Features & Benefits:

- Highest capacity to footprint/ weight ratio
- Up to 3400 GPD from sea water
- Self-contained, plug and play system
- Titanium high pressure pump provides an extended life cycle with salt water compatibility and quiet operations
- Flexible installation and easy to operate
- Globally supported by a network of more than 300 dealers and distributors



## **Special Features**

- 8 inch Color Remote-Mounted Touch Screen
- Real Time Water Quality Monitor
- Screens are Available in Multiple Languages



## **Specifications**

Model #	Fresh Water Production from Sea Water	Water Production from Sea Water	Water Production from Dock Water*	Weight
A400C-1800GPD-1400GPD	1800 GPD   6814 LPD	1400 GPD   5300 LPD	1400 GPD   5300 LPD	413 lbs / 187 kg
A400C-2600GPD-2200GPD	2600 GPD   9842 LPD	2200 GPD   8328 LPD	2200 GPD   8328 LPD	413 lbs / 187 kg
A400C-3400GPD-2900GPD	3400 GPD   12870 LPD	2900 GPD   10978 LPD	2900 GPD   10978 LPD	428 lbs / 194 kg


<sup>\*</sup>Production may vary +/-20% | GPD: Gallons per day • LPD: Liters per day

#### **ELECTRICAL**


Pump				Normal	Start Up	
Motor /HP	Voltage VAC	Hz	Phase	Operating Amps	Current	
Booster 1.5/2	220/380//230/460	50//60	3	4.8/2.4//5/2.5	14/7.2//15/7.5	
Booster 1.5/1	115/230	50//60	3	14.2/7.1//18.2/9.1	54	


	Pump				Normal	Start Up	Circuit
Model #	Motor /HP	Voltage VAC	Hz	Phase	Operating Amps	Current	Breaker Amp
1800/1400	5	190/380//230/460	50/60	3	15.6/7.8//13.4/6.7	47/24//40/20	51/26/46/23
2600/2200-3400/2900	5//7.5	190/380//230/460	50/60	3	16.2/8.1/19/9.5	49/25//57/29	53/27//60/30
1800/1400	5	220/230	50/60	1	24/21.8	72/66	83/73


#### **Dimensions**























WARNING: This product can expose you to chemicals including Di(2-ethylhexyl) phthalate (DEHP), which is known to the state of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov.

© 2019 Parker Hannifin Corporation WPSRC 1-2019

